

OPT 3US TX

OPT MBJ



Three-input OPT-MBJ optical transmitter for distribution of band 3, UHF and full IF-IF signals on a single fibre. Laser optical output level of 5dBm, wavelength 1550nm. (dimensions 135x82x39mm)

Technical Chars

- **OPT 3US TX:** Up to 20dB of manageable optical attenuation (division ratio greater than 1:32 over P.O.N. distribution) when TX is used together with OPT-RX receiver.
- A.B.L.A. Technology: this exclusive FRACARRO system maintains the correct optical level via special independent electronic circuits, even if the RF input level of each input changes
- Dedicated A.B.L.A. status LEDs
- Separate amplification: the new OPT-MBJ optical transmitter works with "separate amplification" and independent handling of the RF input signals
- **Protective shell:** OPT-MBJ optical transmitters and receivers are protected by an innovative protective shell made of flame retardant ABS material (Class V0)
- Optical output level stabilisation even for high variations of the RF input signal
- Monitor output: RF output connector for monitoring the RF signal without disconnecting the service from the distribution network
- Suitable for standard DIN rail mounting (with quick release)
- Low power consumption
- · Power supply status LED
- Quick and easy installation (Plug&Play)
- · High shielding against electromagnetic interference
- Standard SC/APC connectors

OPT 3US TX		
Code		270657
Input RF		3 (3, UHF, IF-IF)
Optical Output		1 SC/APC
Input TV		
Connectors		F Female
Input level	dΒμV	60-85 @MUX
Frequency band	MHz	174-230, 470-790
Return loss	dB	8



MHz	950-2150
	F Female
dΒμV	60-85 @TP
dB	8
nm	1550
dBm	5
dB	>30
	1M
	F Female
MHz	174-230 / 470-790 / 950-2150
dB	59 (VHF), 70 (UHF, SAT)
Vac/Hz	184-264 / 50-60
W	5.5
	Blue on / Signal in the correct A.B.L.A. range, remote feed active
°C	From -10 to +55
	CEI EN 50083-2 EN60065
	1
	8016978103676
mm	176x110x50
mm	135x82x39
Kg	0.345
	dBµV dB nm dBm dB MHz dB Vac/Hz W °C