

Quality TV Signal Meter

SQT784

Now with
12V Antenna Power
Up to 300mA



- ✓ **Colour LCD Display**
- ✓ **Soft Cover Protects Against Drop Damage**
- ✓ **Internal High Energy Lithium-Ion Battery 1800mAh**
- ✓ **High Sensitivity Assists Searching for Weak DTV Signals**
- ✓ **Comprehensive Digital TV Measurements including Level, MER & BER**
- ✓ **Programmed with Australian & European Channel Plans incl. B2 FM Radio**

PRODUCT BENEFITS

- Expanded Channel Plans
- Spectrum Signal Displays
- Now Powers 12V Mast Amplifiers
- Instant Responses to Signal Changes
- Convenient LED Torch Light Integrated
- Audible Lock and Signal Quality Alarm
- Keypad Backlit Enables Use in Darkness
- Sensitive to Weak and Strong TV Signals
- Reads MER, BER and RU with Lock Timer
- Ready for DVB-T2, Exceptional with DVB-T
- Compact Handheld Shape that's Easy-to-Use
- Magnetic Compass Assists Identifying Direction
- Constellation Displays Locked Signals in XY-Plane Scatter Diagrams

SPECIFICATIONS

Terrestrial Tuner & Demodulator

FREQUENCY RANGE	88MHz to 858MHz
INPUT CONNECTOR	F Male for F Female - Female Adapter (included)
SIGNAL LEVEL RANGE	< 30 to 110dB μ V
ANTENNA LINE AMP POWER SUPPLY	12V or 5V at up to 300mA Short Circuit Protected
CHANNEL BANDWIDTH	7MHz Default 8, 6 or 5 MHz Ready

Also available separately SQT784 Battery Car Charger (BC12DC)



SQT784

